

Bluetooth Bracelet mamnal



BLUETOOTH BRACELET MANUAL

1, BUTTON AND LIGHT DEFINE:



LIGHT POWER ON/OFF

2, The Bluetooth bracelet comes with a built-in rechargeable battery. Before use this bracelet, please charge the battery fully (more than 6 hours) for the first time use.

2.1, Plug adaptor to power supplier end

2.2, Normal charging time

Normally, battery of Headset will be fully after being charged about 2 hours. When battery is full, headset will stop charge automatically.

Then, hold the “power on/off” button at 2 seconds for turning on bracelet. (please refer to step of “turn on/off headset” as below.)

2.3, Charging indication

When bracelet is charged, red LED light on. Once battery is full, the LED turn off automatically.

2.5, Standby Time

When the battery is full,
Standby time: 100 hours.

2.6, Low Battery

When the bracelet is on and the battery becomes low, the red LED

will blink and the headset will “beep” every 1 minute. At that time, please recharge the battery as above step.

3, Turn on/off bracelet

3.1, Turn on the bracelet

Hold “power on /off ” button for 2 seconds until the blue LED flash.

3.2, Turn off the bracelet

Hold “power on /off ” button for 4 seconds until the LED turn off.

4, Pairing bracelet with phone

This bracelet is used with Bluetooth built-in mobile phone. Setting up as below:

- Keep bracelet and phone around 1 meter.
- Assure bracelet is turned off
- Hold “power on /off ” button for 4 seconds until the blue and red LED flash alternatively.
- Initiate Bluetooth function of phone, and then search for Bluetooth devices. If it is successful, the mobile phone will show the name of obtained device “BW04 ”. Press “yes ” to pair this bracelet with phone.
- Input ID code of bracelet “ 0000”, Press “Yes ”to complete pairing, then Blue LED will flash 5 times and the bracelet will have a long beep, so that bracelet is under stand-by mode.
and ready for Bluetooth communication .Press locate this bracelet within 10 meters (max.) to phones.

Notice: If pairing process can't complete within 2 minutes, red LED will blink with 3 beep .Finally, bracelet will turn off automatically. Please follow up above steps to repairing again.

5, Link bracelet with phone

Once pairing is successful, bracelet is under stand-by mode.

Owing to different phone has different program, please refer

To procedure as bellow.

When a call is coming or you dial out , phone will link bracelet automatically.If communication between the phone and headset is disconnect , reconnecting procedure is below.

- 1.) Press “power on / off ” button. bracelet will be reconnected to phone and press “Yes” on the phone to accept reconnect mode.
- 2.) Operate phone manual to Bluetooth function and then going into program of paired device and select “BW04 ”

6, To Use Bracelet

When a call is coming, the bracelet will vibrate and lamp flash.

6.2,

7, To Reset the bracelet

You may want to reset the bracelet to original setting. This also clears all current pairings.

- 1.) Assure the bracelet is OFF.
- 2.) Constantly press “power on/off” button until LED blinks red and blue color in turn.
- 3.) Release the “power on/off” button.
- 4.) Hold “power on/off” button until you listen to 2 beeps.
- 5.) Recharge power to the bracelet for a few seconds.
- 6.) The bracelet will turn off and returns to the original setting mode. All of previous pairing data are cleared.

8, Warning :

8.1,bracelet

- Please turn off this bracelet before put it out your hand.
- Do not expose the bracelet under liquid, moisture or humidity as is not waterproof.
- Do not use abrasive cleaning solvents to clean the bracelet.

- Do not expose the bracelet under high or low temperatures.
- Do not expose your bracelet to contact with sharpness objects this will cause scratches and damage.
- Do not stick anything on inside of the bracelet as this may damage internal components.
- If you don't use the bracelet to long periods, be sure to store it in a dry place and far away from extreme temperatures and dust.

8.2, Built-in battery

- Do not attempt to replace the bracelet's battery by yourself as it is built-in recharged battery and we strongly recommend you do not open the case of the battery.
- Only use charger of manufacturer supplied when charging the bracelet.
- Do not use the charger in outdoors or under humid environment.
- Avoid charging the in extremely high or low temperatures.

Product specifications

Bluetooth specification:	Version 1.2
Bluetooth Profile supported	Headset and hands free profile
Rang of Frequency:	2.4GHz Spectrum
Nominal charging time:	within 3 hours
Stand-by time:	up to 60 hours